

#### WESTON ANGULAR WALLPACK 3000K/4000K 13W/18W/28W EMERGENCY

NET-51-11-52







#### **Features & Benefits**

- · Emergency function
- Tri-Wattage driver allows a choice between 13W, 18W or 28W
- Selectable 3000K or 4000K colour temperature
- High efficiency up to 140lm/W
- · IP65 and IK10 rated housing
- · Rear and side cable entry

#### **Key Data**

**Power** 13W/18W/28W

Luminous Flux 1700lm/2500lm/3500lm

Colour Temperature 3000K/4000K

IP Rating IP65
IK Rating IK10

**Dimensions** 319 x 265 x 165mm

Warranty 5 Years (Registration Required)

#### Compatible Accessories

NFT-51-04-59	Photocell Kit for Outdoor Lighting

**NET LED Lighting** 

Buckingway Business Park, 300 Anderson Road, Swavesey, Cambridge, CB24 4UQ



#### **Technical Specifications**

Input Voltage (AC) 220-240V

Power Factor >0.9

Luminaire Efficacy 1251m/W

**LED Manufacturer** Shenzhen Jingrui Photoelectric Co. Ltd.

**LED Type** SMD 2835 **No. of LEDs** 168

Driver ManufacturerSealite Co. Ltd.Total Circuit Power (W)13W/18W/28W

Electrical Class 1

Colour Rendering>80 CRILamp Viewing Angle120°CDimmableNo

Operating Temp. -20°C to +40°C Lifespan LM80 60,000 Hours


UGR Rating 22 Weight 2.2Kg

Manufacturer Sealite Co. Ltd

Luminous Flux Factor 1700lm/2500lm/3500lm

Housing Colour
Housing Material
Battery Pack
Diffuser Material
Emergency Kit
Black
Aluminium
LiFePO4
Polycarbonate
1 Year Warranty

Emergency Operation 3H



#### Other Options

	Description
NET-51-11-50	Weston Angular Wallpack 3000K/4000K 13W/18W/28W Standard
NET-51-11-52	Weston Angular Wallpack 3000K/4000K 13W/18W/28W Emergency

#### **NET LED Lighting**

Buckingway Business Park, 300 Anderson Road, Swavesey, Cambridge, CB24 4UQ






# 3K 4K

### REAR OR SIDE CABLE ENTRY

Protect your wiring from harsh weather and possible tampering


### SELECTABLE COLOUR TEMPERATURE

Choose your colour temperature 3000K or 4000K



## IK65 AND IK10 RATED HOUSING

Protect your fitting from harsh weather and impact



## SELECTABLE WATTAGE

Choose your power setting 13W, 18W or 20W

